

MIA-F10Q module



u-blox F10 standard precision GNSS SiP module

L1/L5 dual-band GNSS receiver module for miniature devices

- 4.5 x 4.5 mm chip-sized module requiring no external components
- Effective multipath mitigation to boost urban accuracy
- Exceptional RF interference immunity with co-located cellular modems
- Proven excellent performance, even with small antennas
- Pin-compatible with previous MIA products for easy migration



4.5 × 4.5 × 1.0 mm



Product description

The MIA-F10Q is built on the u-blox F10 dual-band GNSS technology using L1/L5 GNSS bands, which provides solid meter-level position accuracy in urban areas.

With its proprietary dual-band multipath mitigation technology, u-blox F10 uses the best signals from the L1/L5 bands to achieve a significantly better position accuracy in urban environments than with the L1 band only. Applications like vehicle tracking and micromobility benefit significantly.

MIA-F10Q offers a single antenna input. Two SAW filters in series with a LNA in between provide high robustness against RF interference from co-located cellular modems.

The small, highly integrated system-in-package requires only 20 mm² board space with no need for any external components.

MIA-F10Q is pin-to-pin compatible with previous u-blox generations, which saves designers time and cost when upgrading their designs.

u-blox modules are manufactured in IATF 16949 certified sites and are fully tested on a system level.

MIA-F10Q

	MIA-F10Q
Grade	
Automotive	
Professional	•
Standard	
GNSS	
GPS + QZSS/SBAS	•
Galileo	•
BeiDou	•
NaVIC	•
Multi-band	L1/L5/E5a/B2a
Interfaces	
UART	1
DDC (I2C compliant)	1
Features	
Additional SAW	•
Additional LNA	•
Oscillator	TCXO
Timepulse	1
Power supply	
1.76 V – 3.6 V	•



Product performance

Receiver type	u-blox F10 engine GPS L1C/A, L5 Galileo E1B/C, E5a BeiDou B1C, B2a NavIC L5 QZSS L1C/A, L1S, L1Sb, L5 SBAS L1C/A: EGNOS, GAGAN, MSAS, WAAS	
Nav. update rate ¹	Up to 10 Hz	
Horizontal position accuracy ²	1.0 m CEP (with SBAS) 1.5 m CEP (without SBAS)	
Acquisition	Cold start	28 s
	Aided start	2 s
	Hot start	1 s
Sensitivity	Tracking & Nav.	-167 dBm
	Reacquisition	-160 dBm
	Cold start	-148 dBm
	Hot start	-159 dBm

Tracking features

Odometer	Measure traveled distance with support for different user profiles
Protection level	Real-time position accuracy estimate with 95% confidence

Security features

Signal integrity	RF interference and jamming detection and reporting Spoofing detection and reporting
Device integrity	Receiver configuration lock by command
Secure interface	Signed UBX messages (SHA-256) JTAG debug interface disabled by default

Electrical data

Power consumption at 3 V	3 GNSS: 57 mW
Power consumption at 1.8 V	3 GNSS: 52 mW
Power supply	1.76 V to 3.6 V
Backup supply	1.65 V to 3.6 V

1 = The highest navigation rate can limit the number of supported constellations
2 = Depends on atmospheric conditions, GNSS antenna, multipath conditions, satellite visibility, and geometry

Further information

For contact information, see www.u-blox.com/contact-u-blox.
For more product details and ordering information, see the product data sheet.

Package

53 pin S-LGA (soldered land grid array): 4.5 x 4.5 x 1.0 mm, 0.06 g

Environmental data, quality, and reliability

Operating temp.	-40 °C to +85 °C
Storage temp.	-40 °C to +85 °C
Environmental grade	2015/863/EU RoHS-3
EMC (electromagnetic compatibility)	2014/53/EU RED
Environmental testing	Qualified according to u-blox qualification policy, based on a subset of AEC-Q104
Quality management	Manufactured and fully tested in IATF 16949 certified production sites

Interfaces

Serial interfaces	1 UART 1 DDC (I2C compliant)
Digital I/O	Configurable timepulse 1 EXTINT input for Wakeup
Raw Data output	Code phase data
Timepulse	Configurable: 0.25 Hz to 10 MHz
RTC crystal	For optional connection to external RTC clock
Supported antennas	Active and passive
Protocols	NMEA 4.11, UBX binary

Compatible u-blox location services

AssistNow	Real-time online A-GNSS service with assured global availability
-----------	--

Support products

ANN-MB5	L1/L5 multi-band active GNSS antenna
u-center 2	Highly intuitive software for GNSS performance evaluation

Product variants

MIA-F10Q	u-blox F10 GNSS SiP module, firmware in ROM, 2 SAW filters, LNA, TCXO
----------	---

Legal Notice:

u-blox or third parties may hold intellectual property rights in the products, names, logos and designs included in this document. Copying, reproduction, or modification of this document or any part thereof is only permitted with the express written permission of u-blox. Disclosure to third parties is permitted for clearly public documents only.

The information contained herein is provided "as is". No warranty of any kind, either express or implied, is made in relation to the accuracy, reliability, fitness for a particular purpose, or content of this document. This document may be revised by u-blox at any time. For most recent documents, please visit www.u-blox.com.